



- Battery charger and starter: WET, START-STOP 12/24V battery charger and rapid ignition of all types of vehicles, vans, etc. (570A max).
- Normal charge, boost, rapid ignition selection.
- Display of charging and ignition current.
- Protection against overcharging and pole inversion.

## TECHNICAL DATA

CODE	<b>829392</b>	CHARGE AND STARTING VOLTAG.	<b>12 / 24 V</b>	MIN.RATED REFERENCE CAPAC.	<b>20 Ah</b>
SINGLEPHASE MAINS VOLTAGE	<b>230 V</b>	EFFECTIVE CHARGING CURRENT	<b>105 A</b>	MAX.RATED REFERENCE CAPAC.	<b>1550 Ah</b>
MAINS FREQUENCY	<b>50 / 60 Hz</b>	RATED CHAR.CUR.EN60335-2-29	<b>70 A</b>	ADJUSTMENT POSITIONS	<b>4</b>
CHARGING ABSORBED POWER	<b>2,2 kW</b>	START CUR.1V/C EN60335-2-29	<b>360 A</b>	DIMENSIONS (LxWxH)	<b>32 x 38 x 78 cm</b>
STARTING ABSORBED POWER	<b>12 kW</b>	MAX STARTING CURRENT	<b>570 A</b>	WEIGHT	<b>24 kg</b>

## SUPPLIED ACCESSORIES

712001	COLORADO 150B WORK CLAMP 150A
712002	COLORADO 150R POSITIVE CLAMP 150A

## ON REQUEST ACCESSORIES

BATTERY CHARGERS FUSES	
802029	FUSES 100A 20 PCS

## DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans and light trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- display of charging and starting current
- protection against overloads and polarity reversal.

## DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST



CERTIFICATE

## USEFUL LINKS



VIDEO